RHODE ISLAND COLLEGE

To Answer a Call: Lift handset or press **HANDSFREE** (green key next to handset) or press the **Line** key (small oval green key in ext.window) **Tip:** To switch from handset to **HANDSFREE**, press **HANDSFREE** and replace handset.

To Make a Call: Lift handset or press **HANDSFREE** or press the **Line** key (small green key in extension window). **Internal calls -** dial extension. **External calls -** dial **7** + 1 + Area + Number

Redial: Press line key twice **OR** lift receiver and press line key once.

To Hold a Call: Press HOLD. To return to the caller, press the blinking line key. (*If you press the ringing line before pressing HOLD, don't worry, your caller will be put on HOLD automatically. After 1 minute, a quick beep reminds you that a caller is still on HOLD)*

To Transfer: With a caller on the line, press **TRANSFER** (soft key), dial the internal extension or number. Press **CONNECT** to release the call. (You may consult privately your party before pressing **CONNECT**.)

• To talk to the original calling party press the SWAP key. You may SWAP back and forth until the TRANSFER is complete by pressing CONNECT.

To Conference: With a caller on the line, press **CONFERENCE** (soft key). Dial the next extension or telephone number. When the call is answered, announce the conference and press **CONNECT**. (You may repeat this process for a total of 6 parties, including yourself)

• To talk to the original calling party press the SWAP key. You may SWAP back and forth until the CONFERENCE is complete by pressing CONNECT. **To Forward Calls:** Press **FORWARD** (soft key), dial the extension you want your calls forwarded to and press **DONE** (soft key) again. All calls presented to your extension# will follow your **FORWARD** destination.

To cancel: Press *CHECK FORWARD* and follow soft keys to check number or cancel forward. *To reinstate*: Press *FORWARD*, then press *OK* to keep the last destination or enter a new forward destination, then press *OK*.

Call Pickup: Lift handset and press *PICKUP* (soft key) to answer the ringing telephone in your *Call Pickup* group.

Call Park: With the caller on the line, press *PARK* (soft key) and watch display for park code. Press *OK* (soft key). Retrieve call from any phone by lifting receiver and dialing the *PARK* code.

To Program/Re-label your Autodial Keys

Tip: It is easier to first Re-label your Autodial keys. Once Re-labeled, follow steps to Program Autodial

To Re-Label Autodial:

- 1. Press OPTIONS key at bottom row
- 2. Use Navigator Keys to arrow down to "Change Feature Key Labels", press Select
- 3. Select "Change Feature Key Label"
- 4. Select a Feature Key (Press "Autodial")
- 5. Press **Delete** and enter the name you would like to appear in the display using your keys on the pad for entering ALPHA (letters).
- 6. Press **DONE** when finished see your *Relabeled Autodial* key in the display

Now Follow Steps to Program Autodial

NORTHERN TELECOM 3900 TELEPHONES

To Program Autodial:

- 1. Without lifting handset, press *Autodial*.
- Dial telephone number to be stored (dial the number as you would dial it – don't forget the 7).
- 3. Press Autodial again to save.

To Access Autodial:

- 1. Lift handset or press HANDSFREE.
- 2. Press Autodial.

delete, dial, etc....

Message: Press MESSAGE to access voicemail.

Call Log: copies incoming/outgoing calls automatically

*3904 = 20 incoming /10 outgoing Use navigation keys and soft keys to: select, edit,

Directory: Stores entries by name and phone

number (3904 phones only)

- 1. While on a call, Press COPY.
- 2. Press DIRECTORY (soft key)

3. Use navigation keys and soft keys to: select, edit, delete, dial, etc....

• Stores up to 100 names and phone numbers

Customize your telephone:

Press OPTIONS key to adjust: screen contrast, volume, ring type, time and date format, etc... To exit OPTIONS, press QUIT.

Tip: To turn off XX New Callers message on telephone display: Press Options Key, and using navigation keys, scroll to <u>Call Log Options</u>. Set New Call Indication to OFF. Press DONE to save selection, and QUIT to exit.